

Portable Power for All Applications

PowerVerter® 375-Watt Ultra-Compact Inverter



Model #: PV375

- ▶ 12V DC input; 120V AC output; 2 outlets
- ▶ 375 watts continuous output
- ▶ 600 watts peak output
- ▶ Convenient cigarette lighter plug

DESCRIPTION

Harness your vehicle's battery to efficiently power office equipment on the road. Continuously supplies up to 375 watts of 120V AC power to 2 AC outlets from any 12V battery or automotive DC source. Convenient cigarette lighter DC input jack with 3-ft. cable provides 1-step installation. Portable and compact, the inverter's design is among the most rugged available thanks to its lightweight metal casing.

KEY BUYING POINTS

- Allows users to run AC appliances from any 12V cigarette lighter socket
- Converts 12V DC battery power to 120V AC power
- 375 watts continuous output power; 600 watts peak output power
- 2 outlets
- 3-ft. cord with cigarette lighter plug
- Ultra compact, lightweight design with all-metal housing
- Low battery alarm with auto-shutoff preserves vehicle battery
- Overload alarm with auto-shutoff prevents wattage overload
- Replaceable fuse protects inverter from overload
- Lighted power switch
- 1 year manufacturer's product warranty

TYPICAL APPLICATIONS

- Ideal for laptop computers, portable electronics, battery chargers for cell phones, pagers, notepads, game systems, personal printers and battery rechargers for small battery-operated power tools, portable TV-VCR-stereo systems, camcorders, lighting and other low-power applications under 375 watts.

PACKAGE INCLUDES

- PV375 Inverter
- Warranty information
- Instruction manual

COMPLETE SPECIFICATIONS

SYSTEM OVERVIEW

System overview:	Compact 12 volt DC to 120 volt AC power inverter. 375 watts continuous / 600 watts peak. Cigarette lighter input jack, 2 AC outlets.
Voltage compatibility:	Compatible with 12V DC automotive systems
Frequency compatibility:	60 Hz

OUTPUT

Output watt capacity (watts):	375 watts continuous, supports peak output up to 600 watts for up to 500 milliseconds
Output nominal voltage:	120V nominal
Output voltage regulation:	Maintains PWM sine wave output voltage of 115 V AC (+/- 8 V AC)
Output frequency regulation:	60 Hz (+/- 3 Hz)
Outlet quantity / type:	Includes 2 NEMA 5-15R output receptacles
Overload protection:	Via 40A automotive input fuse

INPUT

Maximum input amps / watts:	Full continuous load - 40A at 12V DC, No load - 0.65A at 12V DC
Input connection type:	12V DC cigarette lighter input plug connection
Input cord length:	3 ft. hardwire input cable, 16 gauge, 2 wire

BATTERY

DC system voltage:	DC input operating range 10-15V DC. Alarm sounds as voltage drops to 10.5V. Auto-shutdown occurs at 10V.
---------------------------	--

LEDS ALARMS & SWITCHES

Alarms:	Dual function alarm indicates overload conditions or low DC input voltage of 10.5V or less.
Switches:	Lighted on/off power switch

PHYSICAL

Shipping weight (lbs):	2.3
Shipping weight (kg):	1.04
Unit weight (lbs):	2.2
Unit weight (kg):	0.99
Unit Dimensions (HWD/in):	2 x 4.25 x 7
Unit Dimensions (HWD/cm):	5 x 10.8 x 17.8
Shipping Dimensions (HWD/in):	11.5 x 7.3 x 2.2
Shipping Dimensions (HWD/cm):	29.2 x 18.54 x 5.59
Material of construction:	Aluminum / sheet metal
Cooling method:	Fan

ENVIRONMENTAL

Operating Temperature:	32-104 Fahrenheit / 0-40 Celcius
Relative Humidity:	0-95% non-condensing

WARRANTY

Product warranty:	1 year (Outside the U.S. and Canada, call for warranty information)
--------------------------	---

SPECIAL FEATURES

Appearance:	Attractive, rugged, metallic blue color inverter system
--------------------	---

*The policy of Tripp Lite is one of continuous improvement.
Specifications are subject to change without notice.
Therefore, your product may vary slightly from what is currently listed.*



Tripp Lite World Headquarters
1111 W. 35th Street
Chicago, IL 60609 USA

Customer Support
(773) 869-1234

© 2007 Tripp Lite. All Rights Reserved.